



## UNIX- ZE2

**HEDBOX UNIX-EZ2 V-LOCK MOUNT PROFESSIONAL CINE BATTERY PLATE WITH 3X D-TAP (14.8V/10A) + 1 X USB (5.1V/2.1A) AND 1X BREAKAWAY 50CM DC12V/3ACABLE WITH 4-Pin FFA 0S 304 Connector SPECIALLY DESIGNED FOR ZCAM CAMERAS**

---

### OVERVIEW:

Hedbox **UNIX-ZE2** V-Lock Mount Professional Cine Battery Plate with 1 x USB (5.1V/2.1A) + 3x D-Tap (14.8V/10A) and **1x Breakaway 50cm DC12V (3A/35W) Cable with 4-Pin FFA 0S 304Connector.**

UNIX Professional Cine Battery V-Mount Plate enables the use of V-Lock battery packs on cameras and/or numerous professional peripherals simultaneously. Featuring a high-quality aluminium v-lock release, Hedbox UNIX plates are designed and tested for up to 10,000 battery cycles.

Three (3) D-Tap DC Power Outputs provide 14.8V/10A for extra devices and peripherals such as on-board recorders, LED lights, monitors, remote follow focus, wireless transmitters etc.

A built-in USB 5V / 2.1A Power Output is located on the top of the UNIX plate.

Designed with versatility in mind UNIX plates have multiple mounting holes to provide universal camera connection or peripheral mounting – 4x M3x12 screws are included with UNIX to mount the plate as required. The **UNIX-ZE2** includes a hard-wired 50cm DC 12V power cable with a **4-Pin FFA 0S 304Connector**, that can be used to mount **ZCAM E2 ; E2C ; E2G ; E2-S6 ; E2-F6 ; E2-F8 ; V1 ; K1**

---

### FEATURES:

#### **Supplied Breakaway 50cm DC Cable with with 4-Pin FFA 0S 304 Connector**

With an installed breakaway DC 12V/ 3A / 35W power cable, UNIX-EZ2 can be used to power various Z CAM cameras like ZCAM E2 ; E2C ; E2G ; E2-S6 ; E2-F6 ; E2-F8 ; V1 ; K1. The breakaway cable is a 50cm long, with 4-Pin FFA 0S 304 Connector.

#### **High Quality Aluminium V-lock release**

Adopting technology that allowed us to use a high-quality aluminum alloy V-lock release, the lock and unlock provides up to 10,000 cycles for a V-mount battery on the Unix plate.

#### **3 x D-Tap DC Power Output**

Unix provides three D-Tap 14.8V / 10A DC power outputs. Three D-taps allow for extra powering for cameras, on board recorders, LED lights, monitors, remote follow focus, wireless transition systems, etc.

#### **Multiple Mounting holes for universal camera connection**

With multiple mounting holes, (4 x M3x12 screws provided) Unix is able to mount on to any device or camera connection.

#### **Build-in USB 5V / 2.1A Power Out Socket**

The USB 5V/2.1A output can be used to power any external USB electronic devices. This function allows you to use the Unix V-lock plate like a power station to charge your cell phone, tablet, or any other electronic devices that can be powered with USB 5V / 2.1A power.

---

### INCLUDED IN BOX:

- 1 X UNIX-EZ2 V-MOUNT PLATE WITH DC12V BREAKAWAY 50CM CABLE WITH 4-PIN FFA 0S 304 CONNECTOR
- 1 X SET SCREW M3X12 (4PCS)
- 1 X USER MANUAL (ENGLISH)
- 1 X 2 YEAR LIMITED MANUFACTURER'S WARRANTY

*For more informations about our complete product range please visit our web site at [www.hedbox.com](http://www.hedbox.com)*



#### SPECIFICATION:

<b>Model :</b>	<b>UNIX-ZE2</b> V-Mount Adapter Power Plate for Z-CAM E2, E2G
<b>Battery Mount :</b>	<b>V-Lock</b> Mount
<b>D-Tap Power Out 1 :</b>	DC 12V ~ 16.8V / 10A / 148W (Max) unregulated
<b>D-Tap Power Out 2 :</b>	DC 12V ~ 16.8V / 10A / 148W (Max) unregulated
<b>D-Tap Power Out 3 :</b>	DC 12V ~ 16.8V / 10A / 148W (Max) unregulated
<b>USB Output :</b>	DC 5V / 2.1A /10W (Max)
<b>Breakaway DC Cable :</b>	<b>DC 12V / 3A / 35W (Max) 50cm (length) with 4-Pin FFA 0S 304 Connector</b>
<b>V-lock release :</b>	High Quality <b>Aluminium</b> Alloy
<b>Operating Temperature :</b>	-20°C to +45°C (-4°F to +113°F)
<b>Dimensions (WxDxH) :</b>	146 x 102 x 26 mm
<b>Weight :</b>	~ 185 g
<b>Mounting :</b>	Multiple mounting holes for universal camera connection



For more informations about our complete product range please visit our web site at [www.hedbox.com](http://www.hedbox.com)